



The
Patent
Office


ABC0
08093

PCT / GB 00 / 02093



INVESTOR IN PEOPLE

PRIORITY DOCUMENT
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH
RULE 17.1(a) OR (b)



The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

10/018762

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

I also certify that by virtue of an assignment registered under the Patents Act 1977, the application is now proceeding in the name as substituted.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.


In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.


Signed

Dated

30 JUN 2000



This Page Blank (uspto)

Patent 1977
(Rule 16)The
Patent
Office17 JUN 99 E455073-1 C06256
P01/7700 0.00 - 9913989.1

The Patent Office

Cardiff Road
Newport
Gwent NP9 1RH

17 JUN 1999

Request for grant of a patent*(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)*

1. Your reference P/61728.GBA/MRC

2. Patent application number
*(The Patent Office will fill in this part)***9913989.1**3. Full name, address and postcode of the or of each applicant *(underline all surnames)*
Patents ADP number *(if you know it)*Marconi Electronic Systems Ltd
The Grove
Warren Lane
Stammore
Middx
HA7 4LY

SECTION 50

APPLICATION FILED 27.1.00.

If the applicant is a corporate body, give the country/state of its incorporation

752406 900 MB

4. Title of the invention AM RECEIVER

5. Name of your agent *(if you have one)*

Gillian Cockayne

"Address for service" in the United Kingdom to which all correspondence should be sent
*(including the postcode)*GEC PATENT DEPARTMENT
WATERHOUSE LANE
CHELMSFORD
ESSEX CM1 2QXPatents ADP number *(if you know it)*6582020 MB
7387467 0016. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and *(if you know it)* the or each application number

Country

Priority application number
*(if you know it)*Date of filing
(day / month / year)

No

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing
(day / month / year)

No

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? *(Answer 'Yes' if:*

Yes

- a) any applicant named in part 3 is not an inventor, or
 - b) there is an inventor who is not named as an applicant, or
 - c) any named applicant is a corporate body
- See note (d))



The
Patent
Office



INVESTOR IN PEOPLE

GB9913989.1

By virtue of a direction given under Section 30 of the Patents Act 1977, the application is proceeding in the name of

MARCONI CASWELL LTD

One Bruton Street

LONDON

IX 8AQ

United Kingdom

Incorporated in the United Kingdom

[ADP No. 07806326001]

the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form

Description (17)

Claim(s) (4)

Abstract (1)

Drawing(s) (2) 2 8

10. If you are also filing any of the following, state how many against each item.

Priority documents (-)

Translations of priority documents (-)

Statement of inventorship and right to grant of a patent (Patents Form 7/77) (3) /

Request for preliminary examination and search (Patents Form 9/77) (1) /

Request for substantive examination (Patents Form 10/77) (-)

Any other documents (please specify) (-)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date 14/6/99

12. Name and daytime telephone number of person to contact in the United Kingdom

T Norris Tel. 01245 27 5133

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

AM RECEIVER

The present invention relates to an amplitude modulation (AM) receiver for amplifying and detecting amplitude modulated radiation and signals.

5

Conventional receivers operable to receive amplitude modulated radiation and generate corresponding demodulated signals, for example receivers such as domestic radios, often incorporate a number of sections; these sections conventionally comprise an antenna for receiving the radiation and generating a corresponding received signal, transmission radio frequency (r.f.) amplifiers for amplifying and filtering the received signal to provide an amplified signal and a detector for demodulating the amplified signal to provide a demodulated output signal. These sections consume significant power when operational, even when operating at reduced power in stand-by mode awaiting incoming radiation, for example awaiting radiation bearing "wake-up-codes" in mobile telephones. This significant power consumption is a problem which limits operating time from a given set of batteries supplying power to the sections. This problem also pertains to radio transponder tags incorporating miniature power cells to provide electrical power thereto, for example as incorporated into identity tags and electronic access keys for automobiles.

10

15

20

25

A further problem arises in conventional receivers where the received signal is often in the order of microvolts and where considerable amplification is required to provide amplified signals of sufficient magnitude to operate detection diodes in detectors of the receivers; such detectors often exhibit cutoff voltages which prevent them from detecting signals presented thereto below a minimum threshold amplitude. Because there is a practical limit to a degree of amplification that can be provided without risking spurious oscillations arising, this

- (b) being more sensitive to the input signal because detection diodes imposing a lower response threshold are not incorporated therein.

Conveniently, detection of the amplified input signal occurs by the transistor providing
5 signal mixing therein. Advantageously, the transistor is operable in a non-linear region of its current/voltage transfer characteristic. This provides the advantage that the amplified input signal is mixed with itself, namely "autoheterodyned", to demodulate it directly to baseband to provide the demodulated signal.

- 10 Advantageously, the transistor functions in its non-linear region at a relatively low supply current, thereby making the receiver more power efficient. Thus, for example, the transistor can be operable to conduct a current therethrough in a range of 5 μA to 100 μA when functioning in its non-linear region.

- 15 In order for the transistor to function simultaneously as a reflection amplifier and as a detector, the transistor is preferably configured so that amplified reflected signals are generated at an input of the transistor for subsequent detection in the transistor; the transistor presents a negative input resistance at its input to achieve this function. In contrast, conventional non-linear mixers employing transmission amplifiers do not generate amplified
20 signals at their inputs and do not then inject them back for demodulation purposes. Conveniently, the transistor incorporates an electrode for receiving the input signal, the electrode being connected through a signal path to a signal earth such that the path is operable to convey reflected signals between the transistor and the signal earth, and to divert the input signal to the electrode.

25

practical limit imposes a lower threshold amplitude for received radiation, and hence a limited operating range, to which the receivers are responsive. This lower threshold amplitude is a problem in some applications, especially where more remote receiver operation is contemplated.

5

In conventional receivers, it is a well known principle that an r.f. transmission amplifier providing a non-linear transfer characteristic can be used as a demodulator for demodulating amplitude modulated signals. This principle was frequently employed in the context of thermionic electron tubes incorporated into radio receivers before a time when silicon semiconductor devices became widely available, the electron tubes functioning as transmission amplifiers.

10

The inventor has appreciated that it is feasible to combine a number of radio receiver sections together to obtain a simplified receiver circuit which counteracts one or more of the problems described above.

15

According to a first aspect of the present invention, there is provided an AM receiver for receiving an input signal and generating a corresponding demodulated signal, the receiver incorporating a transistor biased to be simultaneously operable as a reflection amplifier for reflectively amplifying the input signal and as a detector for detecting the amplified input signal to generate the demodulated signal.

20

The invention provides the advantage that the receiver is capable of:

- (a) consuming less power on account of exploiting reflective amplification, in contrast to transmission amplification employed in the prior art; and

25

According to a second aspect of the invention, receivers according to the first aspect of the invention can be incorporated into a GPS receiver, thereby providing it with relatively reduced operating current consumption and increased detection sensitivity. Conveniently, the GPS receiver incorporates a plurality of receivers according to the invention, receiving
 5 means for receiving input radiation and generating a corresponding received signal, and processing means for filtering, amplifying and gating the received signal to provide input signals for the plurality of receivers to demodulate to provide demodulated signals from which a positional reference for the GPS receiver is derivable.

10 According to a third aspect of the invention, the invention provides a method of amplitude demodulating an input signal using an AM receiver according to the first aspect, the method comprising the simultaneously executable steps of:

- (a) receiving the input signal and reflectively amplifying it in the transistor to generate an amplified input signal; and
- 15 (b) passing the amplified input signal through the transistor operating in a non-linear mode to demodulate it and thereby generate a corresponding demodulated signal.

Embodiments of the invention will now be described, by way of example only, with reference to the following diagrams in which:

20

Figure 1 is a schematic diagram of a first embodiment of an AM receiver according to the invention; and

25 Figure 2 is a schematic illustration of a GPS receiver incorporating the receiver shown in Figure 1.

Referring to Figure 1, there is illustrated an AM receiver indicated by 10. The receiver 10 incorporates a patch antenna 12, a gallium arsenide (GaAs) field effect transistor (FET) 14, a current source 16 and a power source 18. The antenna 12 is connected to a gate electrode 14g of the transistor 14 and also through a link 20 to a signal earth Eg. The power source 18 incorporates an output P connected to a drain electrode 14d of the transistor 14. The transistor 14 also incorporates a source electrode 14s which is connected to a first terminal I1 of the current source 16. A second terminal I2 of the source 16 is also connected to the signal earth Eg. The link 20 and the terminal I2 are both connected at a single point onto the signal earth Eg.

The source electrode 14s is also connected to an output Q whereat a demodulated signal is provided from the receiver 10.

Operation of the receiver 10 will now be described with reference to Figure 1. The transistor 14 is in a grounded gate configuration so that a positive bias provided by the power supply 18 at its output P causes a current I_{FET} in the order of microamperes to flow between the electrodes 14d, 14s and through the current source 16. Preferably, I_{FET} is in a range of 5 μA to 100 μA . The current I_{FET} is sufficiently small for the transistor 14 to operate as a reflection amplifier in a non-linear region of its transfer characteristics. It has been experimentally verified that the transistor 14 provides reflective amplification by measuring a signal gain provided by the receiver 10; it is not possible for the receiver 10 to provide such high amplification if the transistor 14 were functioning as a transmission amplifier. The current source 16 is operable to maintain the transistor 14 biased in the non-linear region.

In its reflection mode of operation, the transistor 14 provides a square law signal transfer characteristic according to Equation 1:

$$i_{FET} = k_0 (v_{gs})^2 \quad \text{Eq. 1}$$

5

where

i_{FET} = small signal change in I_{FET} ;

v_{gs} = small signal change in potential difference between the gate electrode 14g and source electrode 14s; and

10 k_0 = a gain constant.

Assuming to a first approximation that:

$$v_{gs} = k_1 S_R \quad \text{Eq. 2}$$

15

where k_1 = constant,

and that:

$$20 \quad S_R = k_2 S_m \sin \omega_R t \quad \text{Eq. 3}$$

where

k_2 = a constant;

S_m = an amplitude modulating signal;

25 ω_R = angular carrier frequency of the radiation 22; and

The antenna 12 receives incoming radiation 22 and converts it to a received signal S_R . The signal S_R propagates from the antenna 12 to the gate electrode 14g and through the link 20. The link 20 provides an approximately quarter wavelength signal path between the signal earth E_g and the gate electrode 14g at the carrier frequency of the radiation 22; as a consequence, the link 20 does not divert the received signal S_R from the gate electrode 14g because a low impedance presented by the link 20 where it connects to the earth E_g is transferred to an open circuit at the gate electrode 14g. The link 20 also functions as an impedance matching component; its length can be trimmed to afford an impedance match between the transistor 14 and the antenna 12.

10

The transistor 14 operates on the signal S_R in a two stage process, namely the transistor 14:

- (a) amplifies the received signal S_R at its gate electrode 14g by reflection to generate an reflectively amplified signal S_A thereat; and then
 - 15 (b) demodulates the signal S_A , by virtue of the transistor 14 providing a non-linear transfer characteristic, to output a demodulated signal at the source electrode 14s.
- The demodulated signal propagates to the output Q for subsequent processing.

In practice, the two stages (a) and (b) occur simultaneously.

20

In contrast to this two stage process, prior art demodulators do not provide in-situ reflective amplification and simultaneous detection and are therefore relatively less sensitive in comparison to the receiver 10. In contradistinction to the receiver 10, conventional demodulators employing gain devices operating non-linearly to provide amplitude demodulation incorporate the devices configured to function as transmission amplifiers.

25

- (i) it operates on relatively low currents, for example μA ;
- (ii) it provides both amplification and detection directly from high frequencies to baseband;
- (iii) it is capable of operating with signals of relatively lower amplitude than
5 conventional receivers; and
- (iv) it is potentially cheap and requires few component parts.

The advantages make the receiver 10 attractive for use in short distance radio links such as wireless local area computer networks, for remotely interrogatable identification tags, and
10 for use as enhanced performance detectors in mobile telephones and in global positioning system (GPS) receivers.

The receiver 10 provides a synergistic advantage of reflective amplification and detection using a single transistor. Moreover, the receiver 10 is capable of operating at microwave
15 frequencies, for example around 1.5 GHz; experimental results at these frequencies have demonstrated that it can amplify and detect amplitude modulated radiation giving rise to a received signal from the antenna 12 in the order of -80 dBm. The results demonstrate that the receiver 10 is a considerable improvement compared to conventional diode-type detectors which cannot detect such small received signals without considerable transmission
20 amplification being employed to amplify the received signals prior to diode detection.

Applications of the receiver 10 include use as:

- (a) low power receivers for multimode tag devices, for example personnel wearable
25 tags. Conventional multimode tags are capable of transmitting messages in an active

t = time,

then from Equations 1 to 3:

$$5 \quad i_{FET} = k_0 k_1^2 k_2^2 S_m^2 \sin^2 \omega_R t = \frac{1}{2} k_0 k_1^2 k_2^2 S_m^2 (1 - \cos 2 \omega_R t) \quad \text{Eq. 4}$$

If high frequency components, namely at the angular frequency ω_R and higher, are filtered out from the output Q, then the output will be according to Equation 5:

$$10 \quad Q = k_3 S_m^2 \quad \text{Eq. 5}$$

where k_3 = a constant, namely $k_3 = k_0 k_1^2 k_2^2$.

In practice, filtration of the high frequency components will occur in circuits connected to the receiver 10, for example audio amplifiers exhibiting a bandwidth from 50 Hz to 20 kHz, which are not responsive to such components.

Equation 5 corresponds to a demodulated baseband signal at the output Q. Thus, the transistor 14 is capable of providing signal amplification at low operating currents and also providing direct demodulation to baseband.

If the signal S_m is digital binary data, non-linearity implicit in Equation 5 is inconsequential.

The receiver 10 provides the advantages that:

25 :

parking position in a car park incorporating a constellation of low power radio transmitters from which the fobs can derive positional references; and

(c) ultra low power GPS receivers.

5

GPS receivers are well known for use in determining positional references on the earth's surface. A conventional GPS receiver functions by transmitting encoded radiation at a number of carrier frequencies in the order of 1.5 GHz to a constellation of equatorial geostationary satellites and measuring time durations for the radiation to reach the satellites,
10 to be amplified therein and then transmitted therefrom and be received back at the GPS receiver. Each satellite is responsive to radiation in a particular frequency range associated therewith. Distances corresponding to the time durations are calculated in the GPS receiver and geometrical computations then applied to determine a positional reference for the receiver from the distances because the positions of the satellites are known in advance. The
15 radiation emitted by the GPS receiver is encoded by a pseudo-random bit sequence generated within the receiver; this encoding enables the GPS receiver to recognise its radiation transmitted back from the satellites.

Determination of time duration is achieved in the GPS receiver by correlating "early", "on
20 time" and "late" versions of the pseudo-random bit sequence with radiation received back at the GPS receiver. This is necessary in order to ensure signal synchronisation and hence achieve a reliable and accurate time duration measurement.

Referring now to Figure 2, there is shown a GPS receiver indicated by 100. The receiver
25 100 incorporates a circularly polarised antenna 110, a magnetostatic surface wave device

mode at a greater range than they are capable of receiving messages in a semi-passive mode. The active mode has the disadvantage that higher levels of power consumption are associated therewith compared to the semi-passive mode. Conventionally, tag power consumption can be reduced by sampling techniques where the tags enter their active mode for a relatively short period at intervals; use of these techniques results in complex operating protocols for the tags. The receiver 10 is capable of providing, when incorporated into a multimode tag, a highly sensitive "wake-up" receive capability which provides the tag with an enhanced operating range and reduces the need for complex operating protocols;

(b) security receivers for automobiles. Such security receivers incorporating the receiver 10 are capable of:

- (1) exhibiting lower power consumption, for example consuming in the order of tens of μW ;
- (2) being of lower cost; and
- (3) operating at ultra high frequencies (UHF) around 500 MHz to 600 MHz and above compared to conventional security receivers.

Security receivers incorporating the receiver 10 can be operative to communicate security codes, for example "radio keys" allowing authorised access to vehicles and control of immobilisation systems incorporated therein. The receiver 10 is sufficiently simple and compact to incorporate into a key fob, thereby enabling bi-directional communication links to be provided between vehicles and their associated key fobs. Such bi-directional links enable more complex security protocols to be used, thus enhancing security, and permits further added value functions to be added in the fobs, for example memorising an associated vehicle's

The unit 140 comprises three output terminals K_1 , K_2 , K_3 connected to input terminals B_1 , B_2 , B_3 of reflection amplifiers 152, 154, 156 respectively. The reflection amplifiers 152, 154, 156 are incorporated into the assembly 150. The amplifiers 152, 154, 156 also incorporate control terminals C_1 , C_2 , C_3 to which "late", "on time" and "early" control signals are
5 connected from corresponding terminals J_1 , J_2 , J_3 of the measurement unit 178 respectively. These control signals are identical pseudo-random bit streams, namely sequences of data, which are time shifted with respect to one another, usually by a period corresponding to $\frac{1}{2}$ or 1 bit duration in the sequences.

10 The terminals K_1 , K_2 , K_3 are also connected to inputs G_1 , G_2 , G_3 of surface acoustic wave (SAW) filters 162, 164, 166 respectively. The filters 162, 164, 166 incorporate outputs W_1 , W_2 , W_3 which are connected to inputs Z_1 , Z_2 , Z_3 of the receivers 172, 174, 176 respectively. The receivers 172, 174, 176 include outputs D_1 , D_2 , D_3 at which "late", "on time" and "early" signals are output respectively. These outputs D_1 , D_2 , D_3 are connected to
15 corresponding inputs E_1 , E_2 , E_3 of the measurement unit 178 respectively.

The filter/isolator 120 incorporates a thin layer, namely in a thickness range of 10 μm to 100 μm , of yttrium iron garnet (YIG) deposited onto an aluminum or quartz substrate, which provides a signal propagation path through the isolator 120.

20

The SAW filters 162, 164, 166 are operable to delay signals propagating therethrough and also bandpass filter them. The amplifier 130 is arranged to amplify signals received thereat and subsequently reflected therefrom by +23 dB. The receivers 172, 174, 176 are operable to provide +20 dB amplification gain as well as amplitude modulation detection as described
25 above with reference to the receiver 10. The amplifiers 152, 154, 156 are switchable at their

(MSWD) filter/isolator 120, a reflection amplifier 130, a three-way splitter unit 140, an assembly of reflection amplifiers 150, an assembly of narrowband surface acoustic wave filters 160, and an assembly of receivers 170. The assembly 170 incorporates three receivers 172, 174, 176 which are each identical to the receiver 10 in Figure 1. The receiver 100 also incorporates a measurement unit 178 for processing "late", "on time" and "early" outputs generated by the assembly 170 and generating signals at terminals J_1 , J_2 , J_3 for use in the assembly 150. Moreover, the receiver 100 additionally incorporates a computation unit 180 for determining a positional reference by triangulation from time measurements provided by the measurement unit 178 to provide the positional reference as data at a terminal M_0 of the unit 180. Design of the measurement unit 178 and the computation unit 178 will be familiar to one ordinary skilled in the art of GPS receiver design.

The reflection amplifier 130 and the assembly 150 incorporate reflection amplifiers according to our UK patent GB 2 284 323 B whose contents are hereby incorporated by reference with regard to transistors functioning as reflection amplifiers when operating in a linear region of their transfer characteristics. The reflection amplifiers each comprise a FET, namely a silicon JFET or a GaAs device, configured by means of a feedback arrangement such as to operate within a linear region of its current/voltage characteristic such that it reflects a signal received thereat with an increased magnitude.

The antenna 110 incorporates an output S_A which is connected to a first input terminal H_1 of the filter/isolator 120. The filter/isolator 120 incorporates a second terminal H_2 which is connected to an input/output terminal F of the amplifier 130, and also a third terminal H_3 which is connected to an input terminal K_0 of the splitter unit 140.

prominent amplitude when correlation thereof with one or more of the control signals occurs.

5 The signals S_{10} , S_{11} , S_{12} , switched by the amplifiers 152, 154, 156 respectively to be amplified or attenuated, propagate to the inputs G_1 , G_2 , G_3 respectively. The filters 162, 164, 166 bandpass filter and delay the signals S_{10} , S_{11} , S_{12} propagating therethrough to provide corresponding signals S_{20} , S_{21} , S_{22} at the outputs W_1 , W_2 , W_3 respectively. The inputs Z_1 , Z_2 , Z_3 receive the signals S_{20} , S_{21} , S_{22} which pass to the receivers 172, 174, 176 whereat they are amplified and demodulated to provide "late", "on time" and "early" output
10 signals at the outputs D_1 , D_2 , D_3 respectively. The signals D_1 , D_2 , D_3 propagate to the inputs E_1 , E_2 , E_3 respectively of the measurement unit 178.

The unit 178 monitors the inputs E_1 , E_2 , E_3 to identify signals thereat corresponding to correlation of the signals present at the terminals K_1 , K_2 , K_3 with those generated within the
15 measurement unit 178 and output via the terminals J_1 , J_2 , J_3 to the terminals C_1 , C_2 , C_3 respectively. By doing so, the measurement unit 178 determines, by an iterative process, a time duration for radiation emitted from the receiver 100 to propagate to the first satellite and be received again by the receiver 100.

20 The receiver 100 repeats measurements as described above for second and third geostationary satellites to derive three time duration measurements. The measurement unit 178 outputs these measurements to the computation unit 180 which calculates therefrom corresponding distances from which a positional reference is calculated by a process of triangulation to provide positional data at an output M_0 .

25

terminals C_1 , C_2 , C_3 respectively so that each provides +20 dB gain in a high gain state and -20 dB gain in a low gain state.

Operation of the GPS receiver 100 will now be described with reference to Figure 2:

5

The GPS receiver 100 emits from its transmitter units (not shown) connected to the measurement unit 178 encoded radiation to a first geostationary satellite (not shown) which amplifies and transmits the encoded radiation to provide input radiation 190 which is incident on the antenna 110.

10

The antenna 110 receives the input radiation 190, the radiation being C code GPS radiation at 1574.42 MHz frequency, and generates a signal S_1 corresponding thereto. The signal S_1 propagates to the first terminal H_1 of the filter/isolator 120 through which it passes to the second terminal H_2 whereat it is output to the terminal F of the amplifier 130; the filter/isolator 120 is operative to selectively limit components of the signal S_1 whose amplitude exceeds a threshold level, the level determined during manufacture of the filter/isolator 120. The amplifier 130 functions as a negative resistance and reflectively amplifies the signal S_1 to generate a corresponding amplified signal S_2 which propagates from the terminal F back to the terminal H_2 of the filter/isolator 120. The signal S_2 propagates from the terminal H_2 to the terminal H_3 at the filter/isolator 120 whereat it is output as a signal S_3 . The signal S_3 propagates to the input K_0 of the splitter unit 140 which divides the signal S_3 to generate three signals S_{10} , S_{11} , S_{12} at the outputs K_1 , K_2 , K_3 respectively. In response to the control signals applied to the terminals C_1 , C_2 , C_3 , the amplifiers 152, 154, 156 selectively reflectively amplify or attenuate the signals S_{10} , S_{11} , S_{12} respectively; thus, the signals S_{10} , S_{11} , S_{12} thereby become time gated such as to assume a

25

The receiver 10 is operable to inherently additionally provide an automatic gain control (AGC) characteristic for compressing the dynamic range of signals applied to the receiver 10. By appropriate choice of negative resistance exhibited by the transistor 14 at its gate electrode 14g, the current I_{FET} can be arranged to decrease in response to increased input
5 signal strength so that the negative resistance exhibited at the gate electrode 14g changes to provide reduced gain.

By incorporating a frequency-sensitive cutoff filter, for example a bandpass filter, in a signal path between the antenna 12 and the gate electrode 14g, it is feasible to convert the
10 AM receiver 10 into a frequency modulation (FM) receiver for demodulating frequency modulated radiation. The filter is operative, for example slightly off resonance, to provide signal attenuation for signals propagating therethrough in response to frequency change of the signals; such attenuation is manifest as amplitude modulation in signals provided from the filter which the transistor 14 is operative to demodulate. Moreover, because the receiver
15 10 can be adapted to be an FM receiver, it is also capable of functioning as a phase detector for demodulating phase modulated radiation and signals.

In broad overview, the control signals applied to the terminals C_1 , C_2 , C_3 are used to gate the signal S_1 from the antenna 110 to provide the output signals at the outputs D_1 , D_2 , D_3 which are processed by the units 178, 180 for determining the time durations and hence a positional reference for the receiver 100. Determination of the positional reference will be familiar to one ordinarily skilled in the art of GPS receiver design where the output signals at the outputs D_1 , D_2 , D_3 are used to steer a code generator incorporated into the measuring unit 178 for use in synchronisation and hence determining the time durations.

The GPS receiver 100 is capable of operating with lower power consumption compared to conventional GPS receivers. The receiver 100 achieves this lower consumption by exploiting reflective amplification in the amplifier 130, in the assembly of reflection amplifiers 150 and in the assembly of receivers 170. Exploitation of reflective amplification provides an additional advantage of allowing the receiver 100 to be fabricated into a GaAs microwave monolithic integrated circuit (MMIC) connected to associated MSWD and SAW devices. Such a MMIC is potentially a relatively low-cost compact component for incorporation into GPS systems.

It will be appreciated by those skilled in the art that variations may be made to the receiver 10 and to the GPS receiver 100 described in the foregoing without departing from the scope of the invention. For example, the link 20 can be replaced by a filter network operative to bias the transistor 14 to provide reflective gain whilst imparting a narrower passband characteristic to the receiver 10, thereby making it more frequency selective. Moreover, the transistor 14 can be a silicon transistor when the circuit 10 is operable to receive radiation at relatively lower frequencies, for example at VHF frequencies in a range of 100 MHz to 150 MHz.

which is responsive to input signal magnitude, thereby providing the receiver with an AGC characteristic.

7. An FM receiver incorporating an AM receiver according to any one of Claims 1 to 6, the FM receiver further comprising converting means for converting an input frequency modulated signal applied thereto into a corresponding amplitude modulated signal which the AM receiver is operable to demodulate to provide a demodulated output signal.
8. A receiver according to Claim 7 wherein the converting means comprises a band pass filter operable off resonance to convert the frequency modulated signal into the corresponding amplitude modulated signal.
9. A GPS receiver incorporating one or more receivers according to Claim 1, 2, 3, 4, 6 or 7, receiving means for receiving input radiation and generating a corresponding received signal, and processing means for filtering, amplifying and gating the received signal to provide input signals for the one or more receivers to demodulate to provide demodulated signals from which a positional reference for the GPS receiver is derivable.
10. A receiver according to Claim 9 wherein the receiving means is a circularly polarised antenna.
11. A receiver according to Claim 9 or 10 wherein the processing means incorporates reflection amplifiers for amplifying and gating the received signal for generating the

CLAIMS

1. An AM receiver for receiving an input signal and generating a corresponding demodulated signal, the receiver incorporating a transistor biased to be simultaneously operable as a reflection amplifier for reflectively amplifying the input signal and as a detector for detecting the amplified input signal to generate the demodulated signal.
2. A receiver according to Claim 1 wherein the transistor is operative in a non-linear region of its current/voltage transfer characteristic.
3. A receiver according to Claim 2 wherein the transistor is operable to conduct a current therethrough in a range of 5 μ A to 100 μ A to function in its non-linear region.
4. A receiver according to Claim 1, 2 or 3 wherein the transistor incorporates an electrode for receiving the input signal, the electrode connected through a signal path to a signal earth such that the path is operable to convey reflected signals between the transistor and the signal earth, and to divert the input signal to the electrode.
5. A receiver according to Claim 1, 2, 3 or 4 wherein the receiver incorporates an antenna assembly for receiving input radiation and generating therefrom the input signal for the transistor.
6. A receiver according to Claim 1, 2, 3 or 4 arranged to provide a gain therethrough

generate an amplified input signal; and

(b) passing the amplified input signal through the transistor operating in a non-linear mode to demodulate it and thereby generate a corresponding demodulated signal.

19. A receiver substantially as hereinbefore described with reference to Figure 1.
20. A GPS receiver substantially as hereinbefore described with reference to Figures 1 and 2.

processed signals.

12. A receiver according to Claim 9, 10 or 11 wherein the processing means incorporates magnetostatic filtering and frequency selective limiting means for processing the received signal.
13. An identification tag incorporating a receiver according to any one of Claims 1 to 8 operable to be responsive to radio radiation received thereat.
14. A wireless local area network for interconnecting computers, the network incorporating a receiver according to any one of Claims 1 to 8 for performing demodulation of signals within the network.
15. A mobile telephone incorporating a receiver according to any one of Claims 1 to 8 operable to provide demodulation of signals propagating therein.
16. An electronic security key incorporating a receiver according to any one of Claim 1 to 8 for performing demodulation of signals propagating therein.
17. A key according to Claim 16 wherein the receiver is housed within a key fob.
18. A method of amplitude demodulating an input signal using an AM receiver according to Claim 1, the method comprising the simultaneously executable steps of:
 - (a) receiving the input signal and reflectively amplifying it in the transistor to





Fig. 1

ABSTRACT

The invention provides an AM receiver (10) incorporating an antenna (12), a transistor (14), a current source (16) and a power supply (18). The antenna (12) is connected to a gate electrode (14g) of the transistor (14) and through a link (20) to a signal earth. In operation, the antenna (12) receives radiation and generates a corresponding input signal which propagates to the gate electrode (14g). The transistor (14) is operable to process the input signal in two steps, namely to reflectively amplify the input signal to generate a correspondingly reflectively amplified input signal at the gate electrode (14g) in a first step, and amplitude demodulate the amplified input signal in a second step. The transistor (14) is operable in a non-linear region of its current/voltage characteristic whereat it simultaneously provides reflective amplification and signal demodulation, namely the two steps occur simultaneously. In contradistinction, conventional demodulators employing gain devices operating non-linearly to provide amplitude demodulation incorporate the devices configured to function as transmission amplifiers.



PC1/GB0002093
1/6/00

Masconi Intellectual Property

This Page Blank (uspto)